


# Paycloud Sensor Verifone Installation Guide




## Verify you have the required parts as listed below:

1. Paycloud Sensor
2. Transformer
3. Power Adapter (only required for Omni series terminals)
4. Terminal Cable (Verifone)



### STEP 1

Connect the Paycloud sensor to the Transformer as shown in the image to the left.



### STEP 4

**Required for Verifone Omni series terminals ONLY**

Connect the Power Adapter to the Transformer, then to an available wall outlet.



### STEP 2

Connect the Terminal Cable to the Transformer. Verifone uses a standard Ethernet cable. Verifone Vx570 terminals can use a USB cable.



### STEP 5

Once you have verified all connections, plug in the power cable for the terminal. The lights on either side of the sensor should illuminate, indicating that installation was successful.




### STEP 3

Connect the Terminal Cable to the Terminal PINPad Port. The Verifone PINPad Port is located on the rear of the terminal, below the icon of a PINPad.

If using a USB cable, plug the cable into the USB port located on the rear of the terminal.

## Your Paycloud sensor is now ready for use.

# Paycloud Sensor Hypercom Installation Guide



Verify you have the required parts as listed below:

1. Paycloud Sensor
2. Transformer
3. Terminal Cable (Hypercom)



### STEP 1

Connect the Paycloud sensor to the Transformer as shown in the image to the left.



### STEP 2

Connect the Terminal Cable to the Transformer.

Hypercom has a specific cable that must be used as shown in the images to the left.



The cable that plugs into the terminal is the size of a phone connector as seen in the image to the left.



### STEP 3

Connect the Terminal Cable to the Terminal Serial Port. The Hypercom Serial Port is located on the bottom of the terminal as shown in the image to the left.

**WARNING:** DO NOT Connect the Paycloud Sensor to the PINPad Port on Hypercom terminals. Doing so can cause errors in the Application Manager and will require a factory reset.



### STEP 4

Once you have verified all connections, plug in the power cable for the terminal. The lights on either side of the sensor should illuminate, indicating that installation was successful.

**Your Paycloud sensor  
is now ready for use.**